

Алматы (7273)495-231
 Ангарск (3955)60-70-56
 Архангельск (8182)63-90-72
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Благовещенск (4162)22-76-07
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Владикавказ (8672)28-90-48
 Владимир (4922) 49-43-18
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89

Ижевск (3412)26-03-58
 Иваново (4932)77-34-06
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Коломна (4966)23-41-49
 Кострома (4942)77-07-48
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Курган (3522)50-90-47
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Ноябрьск (3496)41-32-12
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Петрозаводск (8142)55-98-37
 Псков (8112)59-10-37
 Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Саранск (8342)22-96-24
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Сыктывкар (8212)25-95-17
 Сургут (3462)77-98-35
 Тамбов (4752)50-40-97
 Тверь (4822)63-31-35

Тольяти (8482)63-91-07
 Томск (3822)98-41-53
 Тула (4872)33-79-87
 Тюмень (3452)66-21-18
 Улан-Удэ (3012)59-97-51
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Чебоксары (8352)28-53-07
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Чита (3022)38-34-83
 Якутск (4112)23-90-97
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://ecoray.nt-rt.ru> || eya@nt-rt.ru

Рентген аппараты для ветеринарии Orange



Model	Orange 9020HF	Orange 1040HF	Orange 1060HF	
Generator Type	High Frequency Inverter			
HV Generator	Max. Output Power	1.35kW (90kV@15mA)	2.4kW (80kV@30mA)	3.2kW (80kV@40mA)
	kV Range	40 - 90kV (1kV Step)	40 - 100kV (1kV Step)	40 - 100kV (1kV Step)
	mAs Range	0.32 - 30mAs (21 Step)	0.32 - 100mAs (26 Step)	0.32 - 100mAs (26 Step)
	Max. kV / mA	90kV / 20mA	100kV / 40mA	100 kV / 60mA
	Maximum programmed mA output by kV level	12, 15, 16, 18, 20mA	20, 26, 30, 35, 40mA	25, 30, 35, 40, 50, 60mA
X-Ray Tube	Focal Spot	1.2 X 1.2mm	1.2 X 1.2mm	2.0 X 2.0 mm
Input Power	110 - 120V / 60Hz	110 - 120V / 60Hz	220 - 230V / 50Hz	
	220 - 230V / 50Hz	220 - 230V / 50Hz	220 - 230V / 50Hz	
Protection	Overload protection of high frequency inverter and X-ray tube			
Collimator	X-Ray Field Size	Min.: 5cm X 5cm at 100cm SID Max.: 27cm X 27cm at 66cm SID	Min.: 5cm X 5cm at 100cm SID Max.: 35cm X 35cm at 66cm SID	
	Lamp	12V 50W, Halogen Lamp		
	Dual Laser	Dual laser spot to 66cm target away		
User Interface	Display	1) 7 segment LED X 2 or 3 digits of kV, mAs 2) Ready, X-ray, Wait, Error LED		
	Operation Switch	1) kV & mAs Up-Down 2) Dual Laser & Lamp ON/OFF 3) Display Reverse 4) APR Memory Storage 5) 8 Memory (Extendable 16 Memory)		
Weight	7.8kgs	12.5kgs	14.6kgs	
Dimension (L x W x H/mm)	Actual size: 275*140*150	Actual size: 344*797*188	Actual size: 344*191*210	
	Packing size: 490*340*310	Packing size: 620*380*340	Packing size: 620*380*340	

* Specifications are subjects to change without prior notice.



Durable &

